

Model: IB-145 - ECO RANGE

400/230 V - THREE-PHASE | 1.500 R.P.M. | 50 Hz

Automatic without ats panel Stand-by Genset V3.



Image for guidance purposes.

PRP

CONTINUOUS POWER: N/A

PRP "Prime Power" norma ISO 8528-1

LTP

STAND-BY POWER: 148 kVA

LTP "Limited Time Power" norma ISO 8528-1

ENGINE

MAKE	MODEL
BAUDOUIN	6M11G150/5

ALTERNATOR

MAKE	MODEL
MECC-ALTE	ECP34-2MC

VOLTAGE	HZ	PHASE	COS Ø	PRP kVA/kW	LTP kVA/kW	AMP. (LTP)
400/230	50Hz	3	0,8	N/A	148,0/118,4	213,62

Rev.: 27/07/2020

Model: IB-145 - ECO RANGE

400/230 V - THREE-PHASE | 1.500 R.P.M. | 50 Hz

ENGINE CHARACTERISTICS

MAKE	MODEL
BAUDOUIN	6M11G150/5

General Data

Power PRP (kWm)	N/A
Power LTP (kWm)	136.1
No. cylinders	6
Cylinder capacity (L)	6.75
Diameter per stroke (mm)	105 x 130
Compression ratio	18
Cooling system	LIQUID
Injection	DIRECT
Suction	TURBO-INTERC.
Series regulator	ELECTRONIC
Fly wheel coupling	3-11.5

Lubrication system

Oil capacity (L)	19
Oil consumption (%)	0.20
Min. alarm oil pressure (bar)	1

Ventilation system

Air cooling flow (m ³ /h)	18270
Combustion air flow (m ³ /h)	526
Max. back pressure for fan (mbar)	1.5

Exhaust system

Exhaust gas flow (m ³ /h)	1419
Exhaust back pressure (mbar)	60
Temp. exhaust gases (°C)	550

Electrical system

VDC (V)	12
Battery (Ah)	120
Engine start-up (kW)	4

Rev.: 27/07/2020

Model: IB-145 - ECO RANGE

400/230 V - THREE-PHASE | 1.500 R.P.M. | 50 Hz

ALTERNATOR CHARACTERISTICS

MAKE	MODEL
MECC-ALTE	ECP34-2MC

General Data

Power PRP (kVA)	135
Power LTP (kVA)	148
Efficiency Alt. 100 %	92.9
Efficiency Alt. 110 %	92.5
No. Poles	4
Voltage regulator	DSR
No. wires	12
Insulation	H
Xd (%)	327.6
X'd (%)	12.8
X	11.1
Degree of protection	IP23

GENERATOR SET CONSUMPTION

% POWER USED	LITRES/HOUR
50%	17.43
75%	25.21
100%	33.1

DIMENSIONS, CAPACITIES, APPROXIMATE WEIGHT

Dimensions (mm)		
LENGTH	WIDTH	HEIGHT
2986	1120	1780

FUEL TANK (LITRES)	WEIGHT (KG)
220	2120

Rev.: 27/07/2020

Model: IB-145 - ECO RANGE

400/230 V - THREE-PHASE | 1.500 R.P.M. | 50 Hz

INMESOL GENERATOR SET

GENERAL DESCRIPTION

The “INMESOL” generator set is an electrical energy generating machine which is used in places where there is **no mains supply** or when there is a MAINS failure.

The mobile elements, distribution belt, fan, etc., and those parts which reach high temperatures during operation, exhaust manifold, etc, include their corresponding protections, in compliance with the requirements of the Machinery Directive **2006/42**.



INMESOL S.L company with ISO 9001 quality certification system for the:

Design, manufacture, marketing and technical assistance of power GENSETS, lighting towers, welding GENSETS, tractor with PTO GENSET and hybrid generation systems.

Europe regulations:

Inmesol power GENSET sets comply with European legislation and were given the CE marking which includes the following directives:

- 2006/42/EC on machinery safety.
- 2005/88/EC on NOISE EMISSIONS by equipment for outdoor use (amends the 2000/14/EC).
- 2014/30/UE on Electromagnetic Compatibility.
- 2014/35/UE on electrical safety, electrical equipment designed to be used within certain voltage limits

International regulations:

Upon request, INMESOL can supply equipment that complies with the International Legislation and Regulations:

- “Technical Regulation on Safety of Machinery & Equipment” No. 753, repealing GOST R standards for exports to Russia.
- Resolution nº 90708 dated August 30th 2013 “Reglamento Técnico de Instalaciones Eléctricas RETIE” issued by the Ministry of Mining and Energy, Section 20.21 Engines and power generators, for exports to Colombia.

Information:

The power ratings are for reference to environmental conditions: barometric pressure 100 kPa, 25°C and 30% relative humidity. These are defined by ISO 8528 and ISO 3046.

PrimePower (PRP) “Main Service” is applicable for power GENSETS that function as main electric power source. It may be overloaded by 10% in limited time points, maximum once every 12 hours.

StandbyPower (LTP) “Emergency Service” applies to power GENSETS that run during Electrical Grid failure. This power may NOT BE OVERLOADED.

Nevertheless, to obtain long engine life, it is recommended that the active power average load (kW) connected to the power GENSET set in any period of 24 hours of operation does not exceed the following values:

- In Main Service 70% of the PRP power.
- In Emergency Service during Electrical Grid failure 80% of the LTP power.

Rev.: 27/07/2020

Model: IB-145 - ECO RANGE

400/230 V - THREE-PHASE | 1.500 R.P.M. | 50 Hz

ER **ECO**
RANGE

Scope of supply

V3 GENSET WITH AMF CONTROL PANEL **WITHOUT TRANSFER SWITCH.** READY TO ADD SEPARATED LTS PANEL.



Engine/alternator monobloc directly connected and installed via silent blocks on a frame made from high tensile electro welded steel profiles that are treated with degreasing liquids and applied with a phosphate coat and Polyester (QUALICOAT) paint.	Starter battery complete with cables to the engine and pole protection.
Canopy of steel sheet sound proofed with fireproof rockwool, and treated with degreasing liquids and applied with a phosphate coat and Polyester (QUALICOAT) paint.	Installation prepared for earthing spike (spike not included).
Fuel tank integrated in the chassis provided with fuel level gauge and fuel lines to the engine.	Security protection for belts and moving parts as well as on electrical component.
Engine with mechanical engine driven pusher fan.	External emergency stop push button.
Residential silencer with -35 db(a) noise reduction with exhaust tube and protection cap.	Self excited and auto regulated alternator.
Thermal and magnetic circuit breaker	Integrated lifting hook for single point lifting with crane.
Battery charge alternator.	Standard electronic speed governor on engines.
	Electric control cubicle with digital control module, automatic mains failure, manual start or remote start on signal.
	Vertical outlet for hot air.

OPTIONS

Earth fault relay.
LTS Panel in metal cabinet.
Sealed chassis.
Manual engine oil extraction pump.
Battery charger for gen set with 12VCC battery (3A).
Battery charger for gen set with 24VCC battery (5A).
Electric engine coolant preheating.

Rev.: 27/07/2020

Model: IB-145 - ECO RANGE

400/230 V - THREE-PHASE | 1.500 R.P.M. | 50 Hz

DSE 6120 MKIII AUTOMATIC CONTROL PANEL WITHOUT ATS PANEL

V3

PROTECTION, DISTRIBUTION AND AUTOMATIC CONTROL panel which starts the generator set when it detects a mains failure and stops it when the mains is restored with the control unit DSE 6120 MKIII. It also starts and stops the group manually via a pushbutton or remote start-up by contact.



Image for guidance purposes.

It has the following:

1. EMERGENCY STOP PUSHBUTTON

2. PROTECTIONS:

Protection fuses for control module

V1 PREWIRED GENSET READY TO INSTALL AMF CONTROL PANEL.

V2 GENSET WITH AMF CONTROL PANEL WITH TRANSFER SWITCH.

V3 GENSET WITH AMF CONTROL PANEL WITHOUT TRANSFER SWITCH. READY TO ADD SEPARATED LTS PANEL.

Rev.: 27/07/2020

Model: IB-145 - ECO RANGE

400/230 V - THREE-PHASE | 1.500 R.P.M. | 50 Hz

DSE 6120 MKIII AUTOMATIC CONTROL PANEL WITHOUT ATS PANEL

V3

3. DSE 6120 MKIII PROTECTION CONTROL MODULE.

LCD SCREEN:

It is equipped with a digital LCD screen, which makes it easy to read the information concerning the ENGINE, ALTERNATOR and LOAD available in several languages. The readings that can be obtained are:

ENGINE:	ALTERNATOR AND CHARGE:	MAINS:
Coolant temperature	Voltages between phases and between phases and neutral.	Frequency
Oil pressure	Intensities	Voltages between phases and neutral (L1-N, L2-N, L3-N).
Turning speed (rpm)	Frequency	Voltages between phases and (L1-L2, L2-L3, L1-L3).
Fuel level	Active Power (kW)	Active Power (kW)
Battery voltage	Reactive Power (kVAr)	Reactive Power (kVAr)
Battery alternator voltage.	Apparent Power (kVA)	Apparent Power (kVA)
Operating hours	Cos phi	Cos phi
Number of start-ups	Active energy meter (kW-h)	

CONTROL OF THE SET:

STARTS and STOPS the set AUTOMATICALLY when mains failure is detected and when it is restored, respectively.

It can also operate MANUALLY a REMOTE STAR.

Breaker control via fascia buttons.

PROTECTION OF THE ENGINE AND ALTERNATOR, WITH THE ALARMS ACTIVATED:

ENGINE:	ALTERNATOR:	MAINS:
Low oil pressure	Low and High Voltage	Low and High Voltage
High coolant temperature	Low and High Frequency	Low and High Frequency
Low and High battery Voltage.	Overload due to Intensity (A)	
Failure of the alternator to charge batteries	Power Overload (KW)	
Low fuel level	Low load	

Engine maintenance alarms for fuel filter, air filter and oil filter

OTHER CHARACTERISTICS:

The real-time clock records the last 100 events.	USB connectivity	ALTERNATIVE CONFIGURATIONS, which open up the working possibilities
"DSE Net" for the connection of expansion modules. The possibilities of adapting the operation of the generator sets to the different current applications are expanded.	Fully configurable via software and PC.	DATA LOGGING. Option to display, either graphically or in editable tables, information on the genset operation.
Extensive number of configurable inputs and outputs.	Communication via USB cable for remote control	Sleep Mode
Configurable alarms and timers.	Programmable clock with multiple maintenance events which can be configured for optimal motor functioning. Weekly and/or monthly programming for up to 8 startups and shutdowns per week.	Option to inhibit start-up by external signal during a specific period.
Internal PLC editor	CAN, MPU & alternator speed sensing (selectable depending on engine type).	Five key menu navigation
Fuel and start outputs configurable when using CAN.	Customisable power up text and images	Backed-up real time clock.
Tier 4 ECO engine support including exhaust fluids & filters		

V1 PREWIRED GENSET READY TO INSTALL AMF CONTROL PANEL.

V2 GENSET WITH AMF CONTROL PANEL WITH TRANSFER SWITCH.

V3 GENSET WITH AMF CONTROL PANEL WITHOUT TRANSFER SWITCH. READY TO ADD SEPARATED LTS PANEL.

Rev.: 27/07/2020

Model: IB-145 - ECO RANGE

400/230 V - THREE-PHASE | 1.500 R.P.M. | 50 Hz

DSE 6120 MKIII AUTOMATIC CONTROL PANEL WITHOUT ATS PANEL

V3

4. PROTECTIONS

MAGNETO. PROTECTION (A)	EARTH LEAK PROTECTION	DISTRIBUTION
250A, 3P	Optional	Direct from circuit breaker

OPTION:

4-Pole Switchboard in metal cabinet independent from the Automatic Panel

V1 PREWIRED GENSET READY TO INSTALL AMF CONTROL PANEL.

V2 GENSET WITH AMF CONTROL PANEL WITH TRANSFER SWITCH.

V3 GENSET WITH AMF CONTROL PANEL WITHOUT TRANSFER SWITCH. READY TO ADD SEPARATED LTS PANEL.

Rev.: 27/07/2020