



Extension Lead & Distribution Boxes Safety Guidance
(HGH-SG-005)

**It is important to read this entire leaflet BEFORE using
Extension Lead & Distribution Boxes.**

The rules and procedures in force where people are at work may require the person responsible for this equipment to carry out a specific risk assessment.



1. Electricity is hazardous and always be used with great care.
2. Water and electricity make a very hazardous combination. Keep electrical equipment away from rain and water.
3. Plan your work and think ahead to make sure you will always be working safely.
4. If you have not used this type of equipment before, familiarise yourself with the cables, plugs and sockets before you connect it to the electrical supply.
5. You must have at least the following items of PPE, RCD if using 240v supply.
6. Particular items of equipment or environments may require a higher level of personal protective equipment.
7. Electrical equipment must not be used by minors, or by anyone under the influence of drugs or alcohol.
8. Electrical equipment is designed for operation by an able-bodied adult. Anyone with either a temporary or permanent disability must seek expert advice before using it.



HAMPSHIRE GENERATORS

Before Starting Work...

Work Area

1. Do not use electrical equipment where there is a danger of explosion. It will ignite fumes from petrol, or gas cylinders.
2. Make sure that the area is clear and safe and that no-one is close by or could cause distraction.
3. Protect other people from any noise and dust the work may produce. Warn others to keep away, put barriers around the work area. You must prevent unauthorised access.
4. Keep electrical equipment away from rain and water.

Operators

1. You may need to wear PPE appropriate to the task you will be performing.
2. Anyone who is working close by will also need to wear appropriate personal protective equipment.
3. Anybody who is working near to you will also need to wear appropriate personal protective equipment.

Equipment

1. Check your equipment, cables, plugs and sockets. If anything is found damaged, do not use it contact the hire company.
2. Check that the plugs and sockets on your cables and distribution boxes match your supply. Do not try to force connections or improvise them.
3. Do not overload a cable or a distribution box by running too many tools off it at the same time. Your distribution box may have four outlet sockets; this does not mean that you can run four items of equipment all together. You must ensure that the current drawn by all of your equipment is not more than the cable (or fuse) can carry.
4. Equipment with a cylindrical yellow industrial plug fitted is designed to run off a special 100v supply. The hire company will have provided a portable transformer if you need to power the equipment from a normal mains 230v supply. If a portable transformer has been supplied, take care not to injure yourself when moving it about – it may be heavier than you think. Equipment designed to run directly from 230v mains will have either a normal square pin plug fitted or a blue industrial plug.
5. Check on how the on/off switch operates – before you switch equipment on, you must know how to stop it.

Excel Power Ltd t/a The Hampshire Generator & UPS Co.
Company Number – 07965307
VAT Number - 131 6682 22
Full Terms and Conditions can be found here -
www.hampshiregenerators.co.uk/terms-conditions





Electrical Safety

Your equipment will only operate on one voltage: it will be 110v or 230v. 110v machines will have a yellow industrial plug fitted. 230v machines will have either a normal square pin plug fitted, or a blue industrial plug. Read the instructions below for your machine.

110V Machines

1. If you are using a portable transformer, plug the transformer directly in to the 240v socket. Do not use any 240v extension cables.
2. If you need to use an extension cable, follow any special instructions given by the hire company. If the hire company have not given any special instructions, you should only use a suitable rated heavy duty 110v extension cable, not longer than 50 metres (160 feet). You must only use an extension cable between the transformer and the machine.
3. Lay the extension cable out carefully avoiding liquids, sharp edges, doorways or windows where it might be trapped, and places where vehicles might run over it. Unroll it fully or it will overheat and could catch fire.
4. Make sure that any extension cable connections are dry and safe.

240V Machines

1. Use a residual current device (“RCD”) plugged directly in to the 230-volt socket. Plug your machine into the RCD. This will help to protect you against electric shock if the cable or machine get damaged.
2. Use the “TEST” button to check that the RCD is working each time you use it. Reset the RCD according to the instructions supplied with it.
3. If you need to use an extension cable, follow any special instructions given by the hire company. If the hire company have not given any special instructions, you should only use a suitable rated heavy-duty cable, not longer than 50 metres (160 feet). Plug it directly into the RCD.
4. Lay it out carefully avoiding liquids, sharp edges, doorways or windows where it might be trapped, and places where vehicles might run over it. Unroll it fully or it will overheat and cold catch fire.

Using Electrical Equipment

1. If you think a cable may be cut or damaged in any way, switch off and unplug at the mains before inspecting it. If the cable attached to the machine is damaged, stop using the machine. Contact the hire company. If an extension cable has been damaged, do not use it again.
2. Take care not to accidentally pull the plug from the socket.

Excel Power Ltd t/a The Hampshire Generator & UPS Co.
Company Number – 07965307
VAT Number - 131 6682 22
Full Terms and Conditions can be found here -
www.hampshiregenerators.co.uk/terms-conditions





HAMPSHIRE GENERATORS

3. Switch off and unplug before leaving the machine unattended.

If your equipment does not work properly, do not attempt to repair it. Contact the hire company.

Excel Power Ltd t/a The Hampshire Generator & UPS Co.
Company Number – 07965307
VAT Number - 131 6682 22
Full Terms and Conditions can be found here -
www.hampshiregenerators.co.uk/terms-conditions

