



P1PE P4000i ELECTRIC START INVERTER GENERATOR

- 3800w maximum output ideal for powering TV's, Laptops, Motorhomes & more
- Rear wheels and front handle for easy transportability
- Push button electric start with Recoil backup
- LCD display for voltage, frequency & hour count
- Safety cut out it prevent overloading
- 230V 3 Pin UK Plug, 12v DC & 5v USB Sockets
- ECO mode lowers the engine RPM to increase fuel economy
- Can be converted to run on LPG

SPECIFICATION

Model	P4000i
Engine Type	Hyundai 4 Stroke
Displacement	210cc
Rated Speed	3600rpm
Starting Method	Push Button Electric / Recoil Backup
Fuel Type	Unleaded Petrol
Fuel Tank Capacity	12l
Fuel Consumption	
Oil Type	Semi-Synthetic 15W40
Oil Tank Capacity	600ml
Continuous Run Time	
Noise Level	68dBA @ 7m
Net Weight	48Kg

Sockets	2 x 230v 3 Pin UK Plug 1 x 12v DC 1 x 5v USB
Rated Output Power	3500w
Max Output Power	3800w
DC Output	12V / 5A
Battery	12v
Battery Amps	5A

Rated Frequency	50Hz			60Hz		
Rated Voltage	220V	230V	240V	110V	120V	220V
Rated Current	4.0A	3.9A	3.75A	8.2A	7.5A	4.0A