

POWERING YOUR *life.*

93001i

WARRANTY: 3 Years

3000
MAX WATTS

2800
RUNNING WATTS

RUN TIME 11.5hrs **NOISE LEVEL** 58dBA

SUPER LIGHTWEIGHT
Weighs **LESS THAN 22kg**

CLEAN ELECTRICITY
Power **SENSITIVE ELECTRONICS**

ULTRA QUIET
Low noise - **HIGH PERFORMANCE**

COLD START
Easy starts in **COLD WEATHER**

PARALLEL READY
Link 2 units for **DOUBLE POWER**

PARALINK

Sockets



12V DC
Automotive



240V 16A
Blue UK plug



2 x 240V 13A
16A-13A Adapter



Para Link
Sockets

Specifications

START TYPE	Recoil
VOLTAGE (V)	240 (UK)
ENGINE SIZE (cc)	149
FUEL TYPE	Petrol
PETROL CAPACITY (L)	4.5
OIL TYPE	10W-30
OIL CAPACITY (L)	0.58
LOW OIL SHUT-OFF	Yes
CERTIFICATION	UKCA, RoHs, EU V

*Specifications, descriptions and illustrations are subject to change without notice.



**CARBON MONOXIDE
AUTO-SHUTOFF**

**ATOM
FUSION**



16A - 13A
240v Adapter



12V DC
Charging Cables



USB
Adapter



Oil
Funnel

Champion's 3000 watt inverter generator is one of the lightest in the industry at only 21.5kg, making portable power easier than ever. Rely on the 149cc engine with a quiet 58 dBA for up to 11.5 hours of run time. The Parallel Kit (sold separately) can increase your output.

Inside the box

GENERATOR
OPERATORS MANUAL
OIL FUNNEL
12V DC BATTERY CHARGING CABLE

What you will Need

PETROL
ENGINE OIL



PACKAGE (gross)
Weight: 23.5kg
Size: 53 x 35 x 50.5cm

PRODUCT (net)
Weight: 21.5 kg
Size: 44 x 29.2 x 45cm

CHAMPION POWER EQUIPMENT EU
Unit 17-18, Bradley Hall Trading Estate
Bradley Lane, Standish, Wigan, WN6 0XQ, UK
www.championpowerequipment.co.uk