



Anker SOLIX


F3000 Portable Power Station

3,072Wh | 3,600W


The Longest-Lasting Essential Home Backup



3,600W Pass-Through Charging



More AC Idle Standby Time



2,400W Solar Recharging

Email: support@anker.com

Note: Product specifications and details are subject to change without notice. Refer to the Anker SOLIX official website for current and accurate information.



LinkedIn



Website

| Anker SOLIX F3000 Portable Power Station

Capacity	
F3000 Capacity	3,072Wh
Expansion Battery Capacity	3,072Wh
Maximum Scalability	3× Expansion Batteries
Output	
AC Output	230V~ 15.7A Max. 3,600W Max, 50 Hz
SurgePad™ Power	4,500W Max
AC Surge Power	7,200W
Car Charger	12VDC, 10A
Anderson Port	13.4 VDC, 30A
Input	
Maximum Input Power ¹	6,000W Max
AC Input Power	Wall Charger Input - 230V~ 13A Max, 2,990W Max, 50Hz
	EV Charger Input - 230V~ 18A Max, 3,600W Max, 50Hz
Solar Input Power	High-PV: 1,600W Max, 165V
	Low-PV: 800W Max, 60V
Other Specifications	
Battery Type	LFP
Battery Life Cycle	80% Efficiency After 4,000 Cycles
Net Weight	41.5 kg
Dimensions (W × H × D)	651 × 300 × 377 mm
Light Bar	Yes
Smart App Control	Yes
UPS	20 ms

¹BP3000 Expansion Battery required.